

Certificate & Quick Reference

Thank-you for purchasing a YouChoos sound decoder!

This certificate provides specific details of your decoder including your unique build number. Each sound decoder I load is individually catalogued and assigned a unique certificate, indicating the load date and an individual code...

Your decoder has unique number: CL33-TEMPLATE-0614

YouChoos Sounds

Class 33 Diesel Crompton

DCC Address: 3



Included in this package:

PART NUMBER	YouChoos Sounds - Class 33 Diesel Crompton YC-CL33
DECODER	MS series - template
SPEAKER	N/A - template

Functions:

FKey	Category	Action
F0fwd:	LIGHT	FOfwd Forward lights
F0rev:	LIGHT	F0rev Reverse lights
F1:	SOUND	Running Sounds
F2:	SOUND	Horn
F3:	LIGHT	FA1
F4:	LIGHT	FA2
F5:	QUICKSEL	Quick-Select (Cold)
F6:	SOUND	Horn 2
F7:	SOUND	Horn 3
F8:	SOUND	Brake Pressure Release 2
F9:	SOUND	Guard's Whistle
F10:	SOUND	Compressor
F11:	SOUND	Cab Door
F12:	SHUNT + HALF SPEED	Shunting Mode / Half Speed
F13:	SOUND	Coupling Up
F14:	SOUND	Lever Clunk
F15:	SOUND	Rail Clack
F16:	SOUND	Wheel Flange
F17:	SOUND	AWS Bell
F18:	SOUND	Horn 4
F19:	SOUND	Mute
F20:	VOLUME	Volume Decrease
F21:	VOLUME	Volume Increase
F22:	SOUND	Horn 5
F23:	SOUND	Horn 7
F24:	SOUND	Announcement
F25:	SOUND	Horn 6
F26:	SPEEDLOCK	SpeedLock
F27:	SOUND	Clag
F28:	SOUND	Clag 2

All functions are ON/OFF.

Feature Notes:

Active Braking – To slow down, choose the desired speed on the throttle, then use the Brake key to control the slow-down to that speed. If you prefer more traditional throttle-based braking, simply decrease the value in CV#4, or even simpler: leave ACTIVE BRAKE switched on all the time!

Shunt Mode – Momentum/Inertia is reduced to 1/4 the normal effect and the throttle range is halved to simulate driving light-engine.

Quick Select – For steam, switches from standard chuff sounds to light-engine where chuffs are quieter. For hybrid locomotives, switches engine type – usually effective only at standstill. Some steam projects contain a 'QuickSelect#2' which normally gives heavier chuffs compared to the default. For diesel, sometimes provided for alternative cold start.

Solo – usually defined on the same key as QuickSelect for light-engine on a steam loco – has various effects including reducing the effect of momentum.

SpeedLock – while the SpeedLock key is switched on, the throttle will control the engine sounds only, and leaves the physical speed of the motor unchanged.

NotchUp – for diesel/electric projects, the NotchUp key will raise the base engine level to notch 1 when standing idle. Switch off to return to idle. Has no effect while in motion. Allows you to manually rev the engine up.

Coast – for diesel/electric sounds, the Coast key brings the base engine level down to idle, regardless of the current speed. Switch off to return to speed-dependent engine level.

LowBeam – for some projects, a LowBeam key is provided which dims the forward-motion headlights.

Mute – Fades all sounds out to silent until unmuted, where sounds will be faded back to their previous level.

Volume Up/Down – Overall volume level will be decreased / increased gradually while VOLUP / VOLDOWN is switched on, eventually reaching silent or the maximum defined in the project (usually around 90%). Affects CV#266 master volume level. If you lose sound, check that you haven't simply reduced the volume to silent! Default is recommended around 65%.

Dynamic / Exponential Inertia – Linear throttle-to-speed response is not particularly realistic, so speed change is exponential as speed increases, simulating slow starts from standstill. Similarly, harder throttle requests will result in faster acceleration. This is all built-in to the project working automatically on your throttle requests.

Looping Sounds – Some sounds are looping and will continue repeating until that function is switched off.

Steam Chuff Rate – Use CV#267 to adjust the chuff rate to match wheel rotation.

Random Sounds – Some sounds may be configured to play at random intervals, usually at reduced volume.

IMPORTANT – WARRANTY INFORMATION!

Damage caused by mishandling, short-circuit, or undue force is NOT covered by warranty. Normally, a repair/replacement charge of approximately £30 + P&P will be levied in such cases. Decoders are delicate, so please handle with care. The most common cause of damage is caused by excessive force on wires, which may result in wires becoming detached, or worse, the entire solder pad coming off (particularly true for the smaller decoders). Also be careful that the coloured coating on the wires does not get pulled back exposing bare wire at the solder pads, thus increasing risk of short-circuit.

More Information on Your Sound Decoder



User Sound Assignments

The following table lists the sound effect files loaded onto your decoder, with their unique sample numbers which are used in CVs to assign a sound to a specific feature. Where a sound has no Function Key listed, this indicates that it is an additional sound included in your project which you can manually assign instead of another sound – for example, an alternative whistle/horn which you can swap in for one of the default ones. Please refer to the supplied CV Table document where you can see which CV is used to assign a sound to each Function Key (starts at CV#513).

Of course there are many more sound files that make up your project, such as engine sounds, braking, set-off etc., but these are not included here – only those that are available as user sounds, assignable to Function Keys.



Random Sounds

Zimo decoders include 8 random sound generators, Z1 to Z8, which are also indicated here along with the sample number assigned to them, and whether they are to be played randomly at standstill, in motion, or both.

Likewise, please refer to the CV Table document supplied with your YouChoos sound decoder to see which CVs are used in random sound definition (CVs#744 to 767 and CVs#315 to 338).

Effect Sound Sample Number	Name	Looping	Function Key(s)	Random Generator	Random at Standstill	Random in Motion
22	Horn		F2 (CV#516)			
23	Horn 2		F6 (CV#528)			
24	Horn 3		F7 (CV#531)			
25	Horn 4	Loops	F18 (CV#564)			
26	Horn 5		F22 (CV#679)			
27	Compressor	Loops	F10 (CV#540)			
28	Coupling Up		F13 (CV#549)			
29	Brake Pressure Release					
30	Cab Door		F11 (CV#543)			
31	Lever Clunk		F14 (CV#552)			
32	Guard's Whistle		F9 (CV#537)			
33	Rail Clack	Loops	F15 (CV#555)			
34	Wheel Flange	Loops	F16 (CV#558)			
35	AWS Bell		F17 (CV#561)			
36	Clag		F27 (CV#694)			
37	Announcement		F24 (CV#685)			
38	Brake Pressure Release 2		F8 (CV#534)			
39	Come to Halt 2					
40	Clag 2		F28 (CV#697)			
41	Brake Pressure Release 3					
42	Horn 6		F25 (CV#688)			
43	Horn 7		F23 (CV#682)			

Remember, you can always reset to the project's original configuration if you make a mess, by sending CV#8=8, though note that the DCC Address of the decoder will also be reset (normally back to 3)!



Physical AUX Outputs

The table below states how the physical outputs (for lighting etc.) are configured in your decoder. Outputs that are assigned for FKey0-12 are achieved with Zimo Extended Function Mapping (where CV#61=97). For any outputs assigned to FKeys above FKey12, Swiss Mapping (also known as Zimo Advanced Mapping) is used instead (not shown in this table).

Physical Output	Wire Colour (if wired)	FKey	Effect / Direction	Notes
F0Fwd	WHITE	FKey0FWD	Constant (simple ON/OFF)	F0fwd Forward lights
F0Rev	YELLOW	FKey0REV	Constant (simple ON/OFF)	F0rev Reverse lights
FA1	GREEN	FKey3	Constant (simple ON/OFF)	FA1
FA2	BROWN	FKey4	Constant (simple ON/OFF)	FA2

CL33-TEMPLATE-0614 - YouChoos Sounds - Class 33 Diesel Crompton

CV List MS series - template – Configuration Values at shipping time

CV	Description	Value	CV	Description	Value	CV	Description	Value	CV	Description	Value
1	Short Address	3	77	Free speed curve	42	150	Experimental motor reg - deviation control	0	270	Longer chuff length at very low speeds	0
2	Starting voltage	1	78	Free speed curve	48	151	Motor brake and reduce motor BackEMF in Consist	0	271	Overlapping effect at high speed	16
3	Rate of acceleration	20	79	Free speed curve	54	152	Dim Mask 2 - FO7-FO12, RiBi	0	272	Blow-off duration	50
4	Rate of deceleration	16	80	Free speed curve	60	153	Stop time after DCC signal loss	0	273	Delayed start after blow-off	20
5	Maximum speed	1	81	Free speed curve	68	154	Zimo configuration part 2	0	274	Blow-off schedule	30
6	Middle speed	1	82	Free speed curve	76	155	FKey for half-speed	12	275	Engine (chuff) sound volume at low speed	175
7	Version Number (Part1)	5	83	Free speed curve	84	156	FKey for deactivating momentum	12	276	Engine (chuff) sound volume at high speed and no-load	150
8	Manufacturer Id / HARD RESET	145	84	Free speed curve	92	157	FKey for MAN function	0	277	Degree of volume change under load for driving (chuff) sound.	25
9	Motor frequency	55	85	Free speed curve	102	158	Sound/RailCom config	0	278	Load change threshold	1
10	EMF Feedback cut-off	0	86	Free speed curve	112	159	Special effects FuncOutput7	0	279	Reaction time to load change	1
12	Operation Types - disable specific protocols	5	87	Free speed curve	124	160	Special Effects FuncOutput8	0	280	Load influence (DIESEL)	10
13	Analog mode active functions F1-F8	3	88	Free speed curve	136	161	Servo outputs: Protocol	0	281	Acceleration threshold for full load sound	1
14	Analog functions and Inertia	195	89	Free speed curve	152	162	Servo 1 - Left stop	49	282	Duration of acceleration sound	50
17	Extended address (byte 1)	0	90	Free speed curve	168	163	Servo 1 - Right stop	205	283	Engine sound volume at full acceleration	255
18	Extended address (byte 2)	0	91	Free speed curve	188	164	Servo 1 - Center position	127	284	Threshold for deceleration sound	1
19	Consist Address - high	0	92	Free speed curve	208	165	Servo 1 - Rotating speed	10	285	Duration of reduced volume on deceleration	50
20	Consist Address - low	0	93	Free speed curve	230	166	Servo 2 - Left stop	49	286	Volume level during deceleration	150
21	Consist functions for F1 - F8	0	94	Free speed curve	252	167	Servo 2 - Right stop	205	287	Brake squeal threshold	55
22	Consist functions F0 & F9-F12 + DC Inertia	0	95	Directional speed trimming - REV	0	168	Servo 2 - Center position	127	288	Minimum driving time before brake squeal	50
23	Acceleration trimming	0	97	Consist FKey	0	169	Servo 2 - Rotating speed	10	289	Thyristor - stepping effect	1
24	Deceleration trimming	0	100	Current asymmetry	0	170	Servo 3 - Left stop	49	290	Thyristor - pitch at medium speed	20
27	Direction dependent stops (Lenz ABC)	0	101	Comparison asym. offset	0	171	Servo 3 - Right stop	205	291	Thyristor - pitch at max speed	100
28	RailCom Configuration	3	105	User CV / Manuld	145	172	Servo 3 - Centre position	127	292	Thyristor - speed step for pitch increase	10
29	Configuration bits - decoder properties	10	106	User CV / Provider Id	13	173	Servo 3 - Rotating speed	10	293	Thyristor - volume at cruising	2
31	Index page - high	0	107	Light suppression on cab side 1 - front	0	174	Servo 4 - Left stop	49	294	Thyristor - volume during acceleration	255
32	Index page - low	0	108	Light suppression on cab side 2 - rear	0	175	Servo 4 - Right stop	205	295	Thyristor - volume during deceleration	1
33	Function mapping F0 forward	1	109	Automatic unilateral light suppression	0	176	Servo 4 - Centre position	127	296	eMotor - highest volume	255
34	Function mapping F0 reverse	2	110	Automatic unilateral light suppression	0	177	Servo 4 - Rotating speed	10	297	eMotor - speed when audible begins	15
35	Function mapping F1	0	111	Emergency stop deceleration rate	0	180	Motor req EMK-difference max	0	298	eMotor - speed for full volume	50
36	Function mapping F2	0	112	Special ZIMO configuration bits	0	181	Servo 1 - FKey assignment	0	299	eMotor - pitch dependent on speed	100
37	Function mapping F3	4	113	EMF reduction - compensation	0	182	Servo 2 - FKey assignment	0	300	Enter OpsMode	0
38	Function mapping F4	8	114	Dimming mask	255	183	Servo 3 - FKey assignment	0	301	Inc/Dec programming of CVs	0
39	Function mapping F5	0	115	Uncoupler control (KROIS and ROCO couplers)	0	184	Servo 4 - FKey assignment	0	302	Start Calibration Mode/Sequence	0
40	Function mapping F6	0	116	Automated uncoupling procedure	0	185	Special assignment for live steam engines	0	303	Switching input 1 - key/options	0
41	Function mapping F7	0	117	Flasher functions	0	186	Pantograph 1 - FKey assignment	0	304	Switching input 2 - key/options	0
42	Function mapping F8	0	118	Flashing mask	0	187	Pantograph 2 - FKey assignment	0	305	Switching input 3 - key/options	0
43	Function mapping F9	0	119	Low beam mask for F6	0	188	Pantograph 3 - FKey assignment	0	306	Switching input 4 - key/options	0
44	Function mapping F10	0	120	Low beam mask for F7	0	189	Pantograph 4 - FKey assignment	0	307	Cornering squeals or reed configuration	0
45	Function mapping F11	0	121	Exponential acceleration	11	190	Brightening up times	0	308	Cornering squeal FKey	0
46	Function mapping F12	0	122	Exponential deceleration	11	191	Dimming down time	0	309	Brake Key	0
49	HLU acceleration	0	123	Adaptive acceleration and deceleration	22	192	Special effects FuncOutput9	0	310	On/off key for engine and random sound	1
50	HLU deceleration	0	124	Shunting key functions and SUSI	2	193	Special effects FuncOutput10	0	311	On/off key for function sound	0
51	HLU limit HU	20	125	Special effects F0FWD	0	194	Special effects FuncOutput11	0	312	Blow-off key	0
52	HLU limit U	40	126	Special effects FOREV	0	195	Special effects FuncOutput12	0	313	Mute key	119
53	HLU limit UL	70	127	Special effects FuncOutput1	0	196	Special effects FuncOutput13	0	314	Mute fade in/out time	0
54	HLU limit L	110	128	Special effects FuncOutput2	0	201	SUSI#1 Configuration	0	315	Minimum interval for random generator Z1	40
55	HLU limit LF	180	129	Special effects FuncOutput3	0	202	SUSI#2 Configuration	0	316	Maximum interval for random generator Z1	100
56	Back-EMF control (P and I values)	55	130	Special effects FuncOutput4	0	203	IN1/IN2 Configuration	0	317	Playback length for random generator Z1	0
57	Voltage reference	0	131	Special effects FuncOutput5	0	204	IN3/IN4 Configuration	0	318	Minimum interval for random generator Z2	45
58	Back-EMF intensity	255	132	Special effects FuncOutput6	0	248	Bootloader version	0	319	Maximum interval for random generator Z2	105
59	HLU delay	5	133	FO4 as Cam sensor Or FO4 as fan of smoke generators of steam engines.	0	249	Bootloader subversion	0	320	Playback length for random generator Z2	0
60	Reduced function output voltage (Dimming)	50	134	Asymmetrical stopping ABC	106	250	Decoder ID	0	321	Minimum interval for random generator Z3	50
61	Special ZIMO function mapping	97	135	Km/h - Speed regulation	0	251	Decoder ID	0	322	Maximum interval for random generator Z3	110
62	Effects dimming	0	136	Railcom mph factor	24	252	Decoder ID	0	323	Playback length for random generator Z3	0
63	Effects cycle	62	137	Smoke generator voltage - standstill	0	253	Decoder ID	0	324	Minimum interval for random generator Z4	55
64	Effects ditch	0	138	Smoke generator voltage - cruising	0	254	Project Number	33	325	Maximum interval for random generator Z4	115
65	Version Number (part2) sub-version	15	139	Smoke generator voltage - acceleration	0	255	SubProject Number High Byte	-2	326	Playback length for random generator Z4	0
66	Directional speed trimming - FWD	0	140	Constant braking distance - config	0	256	SubProject Number Low Byte	-102	327	Minimum interval for random generator Z5	60
67	Free speed curve	4	141	Constant braking distance - distance	20	260	Load Code P1	0	328	Maximum interval for random generator Z5	120
68	Free speed curve	7	142	High speed correction - ABC	5	261	Load Code P2	0	329	Playback length for random generator Z5	0
69	Free speed curve	10	143	High speed correction - HLU	0	262	Load Code P3	0	330	Minimum interval for random generator Z6	65
70	Free speed curve	13	144	Programming and update lock - not in MS	0	263	Load Code P4	0	331	Maximum interval for random generator Z6	125
71	Free speed curve	16	145	Experimental - Alternative motor control method	0	264	Variable low voltage (large scale)	0	332	Playback length for random generator Z6	0
72	Free speed curve	20	146	Compensation for gear back-lash	0	265	Loco type selection	101	333	Minimum interval for random generator Z7	70
73	Free speed curve	24	147	BackEMF I-value (Integral)	0	266	Total volume	75	334	Maximum interval for random generator Z7	130
74	Free speed curve	28	148	BackEMF D-Value (Differential)	0	267	Chuff (using virtual cam)	90	335	Playback length for random generator Z7	0
75	Free speed curve	32	149	BackEMF P-Value (Proportional)	0	268	Switching to real cam sensor	0	336	Minimum interval for random generator Z8	75
76	Free speed curve	36				269	Lead-chuff accentuated	0			

398	Steps to trigger Automatic Coasting	25	472	SMG Group 8 FKey	0	545	F11 looping/short	0	684	F23 looping/short	0	783	PWM slow from auto-run	0
399	Rule 17 speed dependent headlights	0	473	SMG Group 8 MKey	0	546	F12 sound assignment	0	685	F24 sound assignment	37	784	PWM fast from auto-run	0
400	Input mapping for internal F0	0	474	SMG Group 8 Forward 1st AUX	0	547	F12 volume adjust	0	686	F24 volume adjust	0	800	SMG Group 14 FKey	0
401	Input mapping for internal F1	0	475	SMG Group 8 Forward 2nd AUX	0	548	F12 looping/short	0	687	F24 looping/short	0	801	SMG Group 14 MKey	0
402	Input mapping for internal F2	0	476	SMG Group 8 Reverse 1st AUX	0	549	F13 sound assignment	28	688	F25 sound assignment	42	802	SMG Group 14 Forward 1st AUX	0
403	Input mapping for internal F3	0	477	SMG Group 8 Reverse 2nd AUX	0	550	F13 volume adjust	0	689	F25 volume adjust	0	803	SMG Group 14 Forward 2nd AUX	0
404	Input mapping for internal F4	0	478	SMG Group 9 FKey	0	551	F13 looping/short	0	690	F25 looping/short	0	804	SMG Group 14 Reverse 1st AUX	0
405	Input mapping for internal F5	0	479	SMG Group 9 MKey	0	552	F14 sound assignment	31	691	F26 sound assignment	0	805	SMG Group 14 Reverse 2nd AUX	0
406	Input mapping for internal F6	0	480	SMG Group 9 Forward 1st AUX	0	553	F14 volume adjust	0	692	F26 volume adjust	0	806	SMG Group 15 FKey	0
407	Input mapping for internal F7	0	481	SMG Group 9 Forward 2nd AUX	0	554	F14 looping/short	0	693	F26 looping/short	0	807	SMG Group 15 MKey	0
408	Input mapping for internal F8	0	482	SMG Group 9 Reverse 1st AUX	0	555	F15 sound assignment	33	694	F27 sound assignment	36	808	SMG Group 15 Forward 1st AUX	0
409	Input mapping for internal F9	0	483	SMG Group 9 Reverse 2nd AUX	0	556	F15 volume adjust	0	695	F27 volume adjust	0	809	SMG Group 15 Forward 2nd AUX	0
410	Input mapping for internal F10	0	484	SMG Group 10 FKey	0	557	F15 looping/short	8	696	F27 looping/short	0	810	SMG Group 15 Reverse 1st AUX	0
411	Input mapping for internal F11	0	485	SMG Group 10 MKey	0	558	F16 sound assignment	34	697	F28 sound assignment	40	811	SMG Group 15 Reverse 2nd AUX	0
412	Input mapping for internal F12	0	486	SMG Group 10 Forward 1st AUX	0	559	F16 volume adjust	0	698	F28 volume adjust	0	812	SMG Group 16 FKey	0
413	Input mapping for internal F13	0	487	SMG Group 10 Forward 2nd AUX	0	560	F16 looping/short	8	699	F28 looping/short	0	813	SMG Group 16 MKey	0
414	Input mapping for internal F14	0	488	SMG Group 10 Reverse 1st AUX	0	561	F17 sound assignment	35	700	unused	0	814	SMG Group 16 Forward 1st AUX	0
415	Input mapping for internal F15	0	489	SMG Group 10 Reverse 2nd AUX	0	562	F17 volume adjust	0	724	HS switching gear set	0	815	SMG Group 16 Forward 2nd AUX	0
416	Input mapping for internal F16	0	490	SMG Group 11 FKey	0	563	F17 looping/short	0	726	Sound id for trigger 1	0	816	SMG Group 16 Reverse 1st AUX	0
417	Input mapping for internal F17	0	491	SMG Group 11 MKey	0	564	F18 sound assignment	25	727	AUX output to activate with trigger 1	0	817	SMG Group 16 Reverse 2nd AUX	0
418	Input mapping for internal F18	0	492	SMG Group 11 Forward 1st AUX	0	565	F18 volume adjust	0	728	Sound id for trigger 2	0	818	SMG Group 17 FKey	0
419	Input mapping for internal F19	0	493	SMG Group 11 Forward 2nd AUX	0	566	F18 looping/short	8	729	AUX output to activate with trigger 2	0	819	SMG Group 17 MKey	0
420	Input mapping for internal F20	0	494	SMG Group 11 Reverse 1st AUX	0	567	F19 sound assignment	0	730	Sound id for trigger 3	0	820	SMG Group 17 Forward 1st AUX	0
421	Input mapping for internal F21	0	495	SMG Group 11 Reverse 2nd AUX	0	568	F19 volume adjust	0	731	AUX output to activate with trigger 3	0	821	SMG Group 17 Forward 2nd AUX	0
422	Input mapping for internal F22	0	496	SMG Group 12 FKey	0	569	F19 looping/short	0	732	Sound id for trigger 4	0	822	SMG Group 17 Reverse 1st AUX	0
423	Input mapping for internal F23	0	497	SMG Group 12 MKey	0	570	F0 sound assignment	0	733	AUX output to activate with trigger 4	0	823	SMG Group 17 Reverse 1nd AUX	0
424	Input mapping for internal F24	0	498	SMG Group 12 Forward 1st AUX	0	571	F0 volume adjust	0	734	Sound id for trigger 5	0	824	Key inverted by IN1	0
425	Input mapping for internal F25	0	499	SMG Group 12 Forward 2nd AUX	0	572	F0 looping/short	0	735	AUX output to activate with trigger 5	0	825	Key inverted by IN2	0
426	Input mapping for internal F26	0	500	SMG Group 12 Reverse ast AUX	0	573	IDLE sound assignment	0	736	Sound id for trigger 6	0	826	Key inverted by IN3	0
427	Input mapping for internal F27	0	501	SMG Group 12 Reverse 2nd AUX	0	574	IDLE volume adjust	0	737	AUX output to activate with trigger 6	0	827	Key inverted by IN4	0
428	Input mapping for internal F28	0	502	SMG Group 13 FKey	0	575	CHANGEDIR sound assignment	0	738	Reed input 1 sound assignment	0	828	Chuff sound beat for Set+1	0
429	Swiss Mapping Group 1 FKey	0	503	SMG Group 13 MKey	0	576	CHANGEDIR volume adjust	0	739	Reed input 1 volume adjust	0	829	Turbo - min step	0
430	Swiss Mapping Group 1 MKey	0	504	SMG Group 13 Forward 1st AUX	0	577	COMETOHALT sound assignment	5	740	Reed input 2 sound assignment	0	830	Braking distance FWD high	0
431	Swiss Mapping Group 1 Forward 1st AUX	0	505	SMG Group 13 Forward 2nd AUX	0	578	COMETOHALT volume adjust	0	741	Reed input 2 volume adjust	0	831	Braking distance FWD low	0
432	Swiss Mapping Group 1 Forward 2nd AUX	0	506	SMG Group 13 Reverse 1st AUX	0	579	THRYSRATOR sound assignment	8	742	Reed input 3 sound assignment	0	832	Braking distance REV high	0
433	Swiss Mapping Group 1 Reverse 1st AUX	0	507	SMG Group 13 Reverse 2nd AUX	0	580	THRYSRATOR volume adjust - not used	0	743	Reed input 3 volume adjust	0	833	Braking distance REV low	0
434	Swiss Mapping Group 1 Reverse 2nd AUX	0	508	Dimming Group 1 Settings	0	581	SETOFF sound assignment	4	744	Z1 Random sound assignment	0	834	Turbo - reduce dependency on accel	0
435	Swiss Mapping Group 1 Reverse 2ndnd AUX	0	509	Dimming Group 2 Settings	0	582	SETOFF volume adjust	0	745	Z1 Random volume adjust	91	835	Number of Additional Quick Select FKeys	0
436	SMG Group 2 FKey	0	510	Dimming Group 3 Settings	0	583	WATEROUTLET sound assignment	0	746	Z1 Random standstill / motion	72	836	Probability of switchgear sparks	0
437	SMG Group 2 MKey	0	511	Dimming Group 4 Settings	0	584	WATEROUTLET volume adjust	0	747	Z2 Random sound assignment	0	837	Script processes	0
438	SMG Group 2 Forward 1st AUX	0	512	Dimming Group 5 Settings	0	585	EMOTOR sound assignment	6	748	Z2 Random volume adjust	91	840	Analog functions F13-F20	0
439	SMG Group 2 Forward 2nd AUX	0	513	F1 sound assignment	0	586	EMOTOR volume adjust	0	749	Z2 Random standstill / motion	72	841	Analog functions F21-F28	0
440	SMG Group 2 Reverse 1st AUX	0	514	F1 volume adjust	0	587	ROLLING sound assignment n/a	0	750	Z3 Random sound assignment	0	843	Deactivate scripts 9 to 16	0
441	SMG Group 2 Reverse 2nd AUX	0	515	F1 looping/short	0	588	DRIVING SOUNDS volume adjustment	0	751	Z3 Random volume adjust	91			
442	SMG Group 3 FKey	0	516	F2 sound assignment	22	589	SWITCHVALVE sound assignment	0	752	Z3 Random standstill / motion	72			
443	SMG Group 3 MKey	0	517	F2 volume adjust	0	590	SWITCHVALVE volume adjust	0	753	Z4 Random sounds assignment	0			
444	SMG Group 3 Forward 1st AUX	0	518	F2 looping/short	0	591	THRYSRATOR2 sound assignment	0	754	Z4 Random volume adjust	91			
445	SMG Group 3 Forward 2nd AUX	0	519	F3 sound assignment	0	592	THRYSRATOR2 volume adjust	0	755	Z4 Random standstill / motion	72			
446	SMG Group 3 Reverse 1st AUX	0	520	F3 volume adjust	0	593	PANTOSTOP sound assignment	0	756	Z5 Random sound assignment	0			
447	SMG Group 3 Reverse 2ndnd AUX	0	521	F3 looping/short	0	594	PANTOSTOP volume adjust	0	757	Z5 Random volume adjust	91			
448	SMG Group 4 FKey	0	522	F4 sound assignment	0	595	PANTODOWN sound assignment	0	758	Z5 Random standstill / motion	72			
449	SMG Group 4 MKey	0	523	F4 volume adjust	0	596	PANTODOWN volume adjust	0	759	Z6 Random sound assignment	0			
450	SMG Group 4 Forward 1st AUX	0	524	F4 looping/short	0	597	PANTODOWNSTOP sound assignment	0	760	Z6 Random volume adjust	91			
451	SMG Group 4 Forward 2nd AUX	0	525	F5 sound assignment	0	598	PANTODOWNSTOP volume adjust	0	761	Z6 Random standstill / motion	72			
452	SMG Group 4 Reverse 1st AUX	0	526	F5 volume adjust	0	599	TURBO sound assignment	9	762	Z7 Random sound assignment	0			
453	SMG Group 4 Reverse 2ndnd AUX	0	527	F5 looping/short	0	600	TURBO volume adjust - not used	0	763	Z7 Random volume adjust	91			
454	SMG Group 5 FKey	0	528	F6 sound assignment	23	601	DYNAMIC BRAKES - sound assignment	7	764	Z7 Random standstill / motion	72			
455	SMG Group 5 MKey	0	529	F6 volume adjust	0	602	DYNAMIC BRAKES volume adjustment	0	765	Z8 Random sound assignment	0			
456	SMG Group 5 Forward 1st AUX	0	530	F6 looping/short	0	603	CORNERING squeal sound assignment	0	766	Z8 Random volume adjust	91			
457	SMG Group 5 Forward 2nd AUX	0	531	F7 sound assignment	24	604	CORNERING squeal volume adjust	0	767	Z8 Random standstill / motion	72			
458	SMG Group 5 Reverse 1st AUX	0	532	F7 volume adjust	0	611	Reed input 4 sound assignment	0	768	Current sound set selected	0			
459	SMG Group 5 Reverse 2ndnd AUX	0	533	F7 looping/short	0	672	Reed input 4 volume adjust	0	769	Last known drive direction	1			
460	SMG Group 6 FKey	0	534	F8 sound assignment	38	673	F20 sound assignment	0	770	Servo1 last known position	127			
461	SMG Group 6 MKey	0	535	F8 volume adjust	0	674	F20 volume adjust	0	771	Servo2 last known position	127			
462	SMG Group 6 Forward 1st AUX	0	536	F8 looping/short	0	675	F20 looping/short	0	772	Servo3 last known position	127			
463	SMG Group 6 Forward 2nd AUX	0	537	F9 sound assignment	32	676	F21 sound assignment	0	773	Servo4 last known position	127			
464	SMG Group 6 Reverse 1st AUX	0	538	F9 volume adjust	0	677	F21 volume adjust	0	774	Last used rail data format	1			
465	SMG Group 6 Reverse 2ndnd AUX	0	539	F9 looping/short	0	678	F21 looping/short	0	775	Measured kmh/mph values	42			
466	SMG Group 7 FKey	0	540	F10 sound assignment	27	679	F22 sound assignment	26	776	Measured kmh/mph values	26			
467	SMG Group 7 MKey	0	541	F10 volume adjust	0	680	F22 volume adjust	0	777	Measured motor load parameter	0			
468	SMG Group 7 Forward 1st AUX	0	542	F10 looping/short	8	681	F22 looping/short	0	778	Measured motor load parameter	0			
469	SMG Group 7 Forward 2nd AUX	0	543	F11 sound assignment	30	682	F23 sound assignment	43	779	Measured motor load parameter	0			
470	SMG Group 7 Reverse 1st AUX	0	544	F11 volume adjust	0	683	F23 volume adjust	0	780	Measured motor load parameter	0			